

DVR MAIN SCREEN



- Camera/Recording Status**
Top row camera connection.
Bottom row camera recording.
Note: Blinking lights in bottom row indicate motion recording. Solid lights indicate continuous recording.
- View Selection**
Click for live view window (restricted to initial number of cameras installed: 1, 4, 6, 9 16)
- Camera View**
Go To Next Camera View
Automatic Camera Switch
Enlarge Camera Display
- Sensor Output**
Activate/Deactivate onboard relay.
ADVANCED USERS
- Search Features**
Search
Audio/video history search
Smart Search
Audio/video history search - ADVANCED USERS
Setting
DVR configuration - ADVANCED USERS
- Exit DVR Software**
- Emergency Record**
Forces ALL cameras to record at maximum frame rate (Note: If cameras are configured individually, this will override previous settings).



- Date and Time**
- Open: Camera & Image Controls**
- Remote Connection**
- Back up Progress**
- Storage Capacity**
Indicates used & available space
- User Log In/Out**

Factory Default Username and Password:
Username: admin Password: admin

BD1000 DVR SEARCH SCREEN

TO SEARCH

1. Choose the Date you wish to create your video.
2. Select the Hour block in which you want to start your search.
3. If you wish you can select the Minutes in the hour.
4. Choose the number of cameras to view (1, 4, 9 or 16)
5. Use the Search Playback controls to find the event(s) you wish to make a video of. Keep note of the start and end time. Pause playback at the beginning of the time you wish to record.
6. Press the AVI Saving button to start the creation of your video clip.

Image Color Control toggle

1. Calendar view
Days in red have recording

Search Controls
Audio/Video playback controls

5. Search Playback controls

Turn camera text on or off

4. Camera Views **Change camera screen size**

3. Minute indicator

2. Hour indicator

Go to a specific time or date

List bookmarks

Set bookmark for a specific camera, time and date

Current Camera numbers

Camera scroll arrows

Go to CD burn screen directly

6. Save a video clip or clips

Print a screen shot if you have a printer attached

Save a screen shot to file

Exit Search

Save As

Print

AVI Saving

CD Burn

Smart Search

Mode Select

Single-Search

Speed

SEARCH

2011 12

S	M	T	W	T	F	S
4	5	6	7	8	9	10
11	12	13	14	15	16	17
18	19	20	21	22	23	24
25	26	27	28	29	30	31

Date

Surveillance Systems

BIG DOG

AVI SAVING

Start Time: 2012-02-14 09:00:00

End Time: 2012-02-14 09:00:00

Camera: 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16

Save Directory: E:\

AVI Format MP4 Format MP4+EXE Format

Burn these files on the CD

Message

Start Stop Close

TO CREATE YOUR VIDEO

NOTE - Time is Military time and listed in year, month, day, hours, minutes and seconds.

- Set the correct Start Time if you did not pause playback at the correct time.
- Set the correct End Time
- Select the Camera or Cameras you wish to make a video of this time frame.
- Your Save Directory should already be set.
- The preferred video format is MP4+EXE
- Select the "Burn these files on the CD" box turning it blue
- Press "Start" and wait for message box to say "AVI Save End"
- You will be automatically taken to the CD/DVD burn screen next.

TO SAVE YOUR VIDEO TO CD OR DVD

- Your Volume Label is automatically set to today's date. Device List will show the DVD drive.
- The video files you created will be listed by File Name.
- If you have already inserted your CD or DVD the Disc Free Size will be listed and shown
- Click "Burn!" and follow the on screen prompts.

CD/DVD Burn

Volume Label: 2012-02-14

Device List: I:\[HAS124 B]

File Name	File Size
Cam01[12_00_12_02_01].EXE	3,052 KB

Total File Size: 3,052 KB

Disc Free Size: 0 KB

Make Folder:

Buffer: Empty 100

Writing: 0% 100

Close Add File Add Folder Delete Delete All Reload Burn!